

Datasheet SLAM Hornet Neos EM 1LED EXIT



| Manufacturing date | 7/2022 | | |
|---|--|--|--|
| Product description | Explosion protected portable luminary with battery back-up (EM) | | |
| ATEX, UKCA & IECEx marking | Ex II 2 G Ex eb ib mb op is IIC T4 Gb Ex II 2 D Ex tb op is IIIC T90°C Db (subject to type of socket) | | |
| Temperature classification | T4 (internal) T90°C (external) | | |
| Operating temperature | -40°C +50°C | | |
| Light source | 1 LED module with SafeEye® technology | | |
| Light emitted at source | up to 2825 lm with battery back-up operation up to 20 % of normal, app. 530 lm | | |
| Luminous flux | up to 1595 lm with battery back-up operation up to 20 % of normal, app. 300 lm | | |
| Colour temperature | 5000 K +/- 10 % | | |
| Colour rendering index | >80 | | |
| Photobiological safety | Exempt group (No marking required, safe in normal use) | | |
| Supply Voltage (min-max) | 100-250VAC/DC, 0/50/60Hz or 20-50VAC/DC, 0/50/60Hz | | |
| Supply Current (typical) | 230V~0,2 A 110V~0,4 A 24 V~1,3 A | | |
| Electrical class | Class 1 (100-250V), Class 3 (20-50V) | | |
| Input power (P) | < 30 W | | |
| Power factor | 0,83 - 0,98 (subject to supply voltage and components used) | | |
| Cable | Standard cable H07BQ-F | | |
| Plug and socket | 2P + Earth (110-230V) 2P+E, 3P, 2P (24-42V) | | |
| Enclosure | Dissipative materials (PC & TPE) | | |
| Ingress protection | IP66 (A-VERSION) IP54-IP66 (C-version, IP rating is subject to type of socket) | | |
| Weight (without cable, socket and plug) | 3,1kg | | |
| EM | Li-lon battery for back-up function (EM) Back-up operation time up to 3h Battery charging time from empty to full ~11h Battery life-time 3-4 years or 600 charging cycles Main light will shortly blink every 15s when lamp is in the EM mode. | | |
| Operation functions | Push Power failure Push Power failure Power failure Indication LED = ON Luminaire = OFF Charging = ON Power failure Power failure Indication LED = ON Luminaire = OFF Charging = ON Power failure Power failure Power failure Power failure Power failure Indication LED = ON Luminaire = ON Charging = ON Charging = ON Power failure Power fai | | |
| Other features | ON/OFF Switch (ib- explosion protection) | | |
| Accessories | SLAM Click'n Fix magnetic fixing system Protective film with EXIT print | | |





Datasheet SLAM Hornet Neos EM 1LED EXIT



Warranty

You will find detailed warranty conditions from www.atexor.com/downloads/warranty

| | Dimensions / mm | |
|--------------------------------|-----------------|-----|
| Product model | L | Ø |
| SLAM® Hornet Neos EM 1LED EXIT | 725 | 125 |







